CO-8ZBS Carbon Monoxide Detector





The CO-8ZBS is a wireless ZigBee Carbon Monoxide Detector designed to detect the presence of Carbon Monoxide to ensure the safety of your family and your house. It detects the carbon monoxide that you can't see, smell or taste in the air. More, CO-8ZBS uses electrochemical carbon monoxide sensor, capable of detecting Carbon Monoxide concentration as low as 50 ppm. According to the different levels of CO concentration detected, CO-8ZBS will notify the Control Panel in different time length and raise alarm with its built-in siren.

CO-8ZBS is compliant with EN50291 standard. With battery-operated feature, you will have peace of mind that the alarm will continue to work even when the power goes out. Completely wireless, the CO-8ZBS easy-to-install alarm can be mounted anywhere in your home and easily blend in with your home decoration while providing reliable 24-protection for your family.

Features

- · Detection Method: Electrochemical CO sensor
- Randomized supervision signals for system integrity checking
- · Low Battery detection

- Test button to test range and silence alarm
- · Loud 85dB built-in siren for audio alerts
- Compatible with other manufacturers' ZigBee systems
- EN50291 compliance

Specifications

| Communication Protocol | ZigBee Pro Home Automation 1.2 |
|------------------------|---|
| Frequency | 2.4GHz |
| Power Source | Alkaline AA x 3 |
| Battery Life | 2 years* |
| Measuring Range | 0 to 999 PPM |
| Alarm Concentration | 30 to 999 PPM |
| Response Time | < 3 minutes for a concentration of 300PPM |
| | 10 – 40 minutes for a concentration of 100PPM |
| | 60 – 90 minutes for a concentration of 50PPM |
| Siren Output | 85dB @ 1 meter |
| Operating Temperature | -10°C to 45°C (14°F to 113°F) |
| Operating Humidity | Up to 85% non-condensing |
| Dimensions | 130mm x 100mm x 41mm |
| Standard Compatible | EN50291 |

^{*} Note: Actual battery life may vary with product settings, operating environment, and usage.